



4x1 DVI KVM Multiview Switcher



EXT-DVIK-MV-41

Interface four computers to one dual-screen workstation

The EXT-DVIK-MV-41 is the perfect solution for controlling four computers from a dual monitor workstation. The operator can observe up to 4 pictures on one screen, while a second monitor can be switched to display the picture that needs closer attention. This product is HDCP compliant, supporting input and output resolutions up to 1920 x 1200 (WUXGA) and 1080p Full HD. The two front panel USB ports and/or Bi-Directional audio (mic and headphones/speaker) can be independently routed from any of the four computers to the workstation.

Four default factory presets provide most commonly used arrangements of windows on a display, including single window output, Picture-In-Picture, Quad view, and Picture-And-Picture. The 4x1 DVI KVM Multiview Switcher is controllable via front panel, keyboard/mouse, and RS-232. An intuitive on-screen Graphical User Interface simplifies system configuration and operation. Up to 8 DVI KVM Switchers can be daisy-chained together to create an elaborate 32 computer workstation. This product is field firmware upgradable with the Gefen Syner-G™ software suite.

How It Works

This product can be placed on a shelf or mounted in a standard 19-inch rack. Connect DVI video output, USB, L/R audio output, and microphone input from up to four computers to DVI-D In, USB Host, L/R In, and Mic ports for Source 1 through 4 on the back panel of EXT-DVIK-MV-41. Connect up to two DVI displays to the Video A DVI-D and Video B DVI-D Outputs. Connect a pair of headphones or powered speakers to the L/R Out audio output. Connect a mono PC microphone to the Mic jack. Connect a keyboard and a mouse to the Workstation USB ports on the back of the unit. Two USB peripherals can be connected to the USB ports on the front of the switcher. If rack-mounting the unit, securely connect the Grounding Terminal to the system ground by 16 AWG or larger diameter copper wiring. Connect the included 12V DC power supply to the unit's 12V DC power supply jack and to an available electrical outlet. To power on the KVM switcher by flipping the Main switch to on position. The switcher can be controlled by using the front panel push-buttons, keyboard/mouse, or via RS-232. To control the switcher via RS-232, connect an automation controller to RS-232 In. To cascade the KVM Switchers together to create an expanded system, connect the RS-232 output from the first unit to the RS-232 input of the next unit until all units are daisy-chained. Up to 8 EXT-DVIK-MV-41 Switchers can be connected together to form an elaborate 32 computer system controlled by a single set of keyboard and mouse. The Power LED on the front of the switcher will glow blue when the unit is powered-on. The Video, Audio, and USB LED indicators will glow in blue when the corresponding input is selected.

Features*

- Dual Screen Workstation Set-up: Full Screen and Multiview
- 4 Multiview Modes: Full Screen, Quad-View, PIP (Picture-In-Picture), and PAP (Picture-And-Picture)
- Input and Output resolutions up to 1920 x 1200 (WUXGA) and 1080p Full HD
- HDCP 1.4 Compliant
- Controlled via front panel, keyboard/mouse, and RS-232.
- Comprehensive and easy-to-use On Screen Display.
- Supports cascading of up to 8 units to create a 32 computer system controlled from one keyboard/mouse workstation.
- Firmware update via USB port using the Gefen Syner-G™ software
- Locking power supply connector
- Rack-mountable using the included brackets

Specifications*

- Maximum Pixel Clock: 165 MHz
- Maximum TMDS Clock: 225 MHz
- Video Input Connectors: (4) DVI-I, 29-pin, female (digital only)
- Video Output Connectors: (2) DVI-I, 29-pin, female (digital only)
- USB Connectors:
 - Front Panel: (2) Type A, 5V DC at 1A maximum shared current
 - Rear Panel: (2) Type A, 5V DC at 1A maximum shared current
 - Rear Panel: (4) Type B
- Microphone Input: (1) 3.5mm mini-mono jack
- Microphone Outputs: (4) 3.5mm mini-mono jacks
- L/R Audio Inputs: (4) 3.5mm mini-stereo jacks
- L/R Audio Output: (1) 3.5mm mini-stereo jack
- RS-232 Input Port: (1) DB-9, female
- RS-232 Output Port: (1) DB-9, male
- Main Power Switch: (1) toggle, on back panel
- Chassis Ground Connection: (1) machine screw, on back panel
- Front Panel Controls: (10) tact-type, blue backlight, (6) tact-type
- Power Indicator: (1) LED, blue
- Video B Indicators: (4) LEDs, blue
- Audio Indicators: (4) LEDs, blue
- USB Indicators: (4) LEDs, blue
- Power Supply Connector: (1) 3-pin, locking
- Power Supply: 12V DC
- Power Consumption: 40W maximum
- Operating Temperature: +32 to +122 °F (0 to +50 °C)
- Operating Humidity: 5% to 90% RH, non-condensing
- Storage Temperature: -4 to +185 °F (-20 to +85 °C)
- Storage Humidity: 0% to 95% RH, non-condensing
- MTBF: 50000 hours
- Dimensions (excluding connectors, W x H x D):
 - 17.2" x 1.2" x 7.9" (437mm x 30mm x 200mm)
- Net Unit Weight: 3.7 lbs (1.6 kg)

 This product has been specifically designed for use with the Gefen Syner-G™ Software Suite, available for download at www.gefen.com. The Gefen Syner-G™ interfaces with the EXT-DVIK-MV-41 via USB and simplifies in-field firmware updates.



Gefen, LLC
 20600 Nordhoff Street, Chatsworth CA 91311
 Tel. (818) 772-9100 (800) 545-6900 Fax (818) 772-9120
www.gefen.com

* Features and specifications are subject to change without notice.
 All trademarks and registered trademarks are the property of their respective owners.
 Copyright© 2014 Gefen LLC